



Updating the Firmware of JETI specbos

1. Start the programming tool JETI_FirmProg.exe



2. Connect the spectrometer unit via USB port to the PC
3. Select the Processor type: M16P
4. Select the correct COM port (in case of problems: check the COM port number in the device manager)
5. Download the appropriate firmware file, unzip it and select the resulting mot file after pressing **Select file...**
6. Start the programming by pressing the **Program device** button



7. Wait until the memory is programmed/ verified and click **OK**



8. Close the program by clicking the **Quit** button

